

ЛАМПЫ ПРОЖЕКТОРНЫЕ

Тип лампы	Напряжение В	Мощность Вт	Световой поток, лм	Средняя продолжит. горения, ч	Габариты, мм		Тип цоколя	Рис.	Кол-во в упаковке шт
					L	D			
ПЖ 24-1000	24	1000	28500	150	190	132	S39/46x47	1	9
ПЖ 26-200	26	200	4500	50	115	66	1Ф-С34-1	10	120
ПЖ 50-500-1	50	500	11100	560	185	68	P40s/41	2	40
ПЖ 75-600	75	600	13400	250	185	68	P40s/41	2	40
ПЖ 110-500	110	500	10500	170	140	65	E27/30	6	100
ПЖ 110-1000	110	1000	22200	150	245	71	E40	3	40
ПЖ 127-500	127	500	8500	400	195	112	P40s/41	4	15
ПЖ 127-1000	127	1000	19000	125	195	112	P40s/41	4	15
ПЖ 127-1000-1	127	1000	19000	125	195	112	E40	6	15
ПЖ 220-400	220	400	5000	200**	180	91	P40s/41	4	36
ПЖ 220-500	220	500	10500	170	140	65	E27/30	6	100
ПЖ 220-500-4	220	500	7600	400	195	91	P40s/41	5	36
ПЖ 220-500-5	220	500	7600	400	195	91	E40	6	36
ПЖ 220-600	220	600	9300	200**	195	112	P40s/41	4	15
ПЖ 220-1000	220	1000	21000	200	245	71	E40	3	40
ПЖ 220-1000-2	220	1000	21000	200	195	91	E40	6	36
ПЖ 220-1000-4	220	1000	18550	100	195	112	P40s/41	6	15
ПЖ 220-1000-5	220	1000	18550	100	195	112	E40	6	15
ПЖ 220-1100	220	1100	17350	200**	220	132	P40s/41	4	9
ПЖ 230-1000	230	1000	17200	500	230	134	P40s/41	7	10
ПЖЗ 24-200	24	200	4500	70	98	61	B24s-3	9	120
ПЖЗ 24-250-3	24	250	5800	100	145	81	P40s/41	8	50
ПЖЗ 24-500-3 *	24	500	13200	150	170	112	P40s/41	8	18
ПЖЗ 24-1000	24	1000	23000	150	190	132	S39/46x47	1	9

** - минимальная продолжительность горения, ч




Рис. 1




Рис. 2



Рис. 3




Рис. 4




Рис. 5




Рис. 6




Рис. 7




Рис. 8




Рис. 9